



Part number	Dimension(mm)							
	A	B	C	D	2E	2F	G	H
POT7/4	7.24±0.15	5.74 min.	2.9±0.1	1.09±0.1	2.9±0.15	4.1±0.1	4.72 Ref.	1.5±0.15
POT9/5	9.15±0.15	7.68±0.15	3.8±0.1	1.95±0.15	3.75±0.15	5.35±0.15	5.65±0.15	2.15±0.15
POT11/07	11.1±0.2	9.2±0.2	4.6±0.1	2.05±0.1	4.6±0.2	7.0±0.2	7.45±0.25	2.2±0.2
POT14/08	14.0±0.2	11.85±0.25	5.85±0.15	3.10±0.1	5.8±0.3	8.361±0.2	9.8 Ref.	3.4 Ref.
POT18/11	18.0±0.4	15.1±0.3	7.4±0.15	3.1±0.15	7.4±0.3	10.6±0.2	11.9±0.2	4.2 Ref.
POT22/13	21.6±0.4	18.2±0.3	9.25±0.15	4.55±0.15	9.4±0.2	13.4±0.4	15.0±0.4	3.8 Ref.
POT26/16	25.5±0.5	21.6±0.4	11.25±0.15	5.5±0.15	11.2±0.3	16.1±0.3	18.75±1.25	3.8 Ref.
POT30/19	30.0±0.5	25.4±0.4	13.3±0.2	5.55±0.15	13.2±0.4	18.8±0.3	21.65 Ref.	4.0±0.3
POT36/22	35.6±0.6	30.4±0.5	15.9±0.3	5.45±0.15	7.5±0.15	10.9±0.2	26.2 Ref.	4.9 Ref.

## POT Cores

For compact transformer  
 Low distortion broadband transmission  
 at low signal modulation  
 DC/DC converters

Part number	C1 (mm <sup>-1</sup> )	Le (mm)	Ae (mm <sup>2</sup> )	Ve (mm <sup>3</sup> )	Weight (g)/set	SM023 AL(nH/N <sup>2</sup> )±25%
POT7/4	1.41	9.9	7	69	0.5	900
POT9/5	2.13.	20.20	9.50	191.90	2.00	950
POT11/07	0.95	16.20	17.00	275.40	2.10	1700
POT14/08	1.16	19.50	16.90	329.55	2.90	2050
POT18/11	0.60	25.80	43.30	1117.14	8.00	3100
POT22/13	0.50	31.50	63.40	1997.10	12.70	4500
POT26/16	0.42	38.50	91.70	3530.45	22.00	4800
POT30/19	0.35	46	133	6118	37	5600
POT36/22	0.3	54.3	184	9991.2	59	8700

\*All specifications are subject to change without notice.

