



Part number	Dimension(mm)							
	A	B	C	D	E min.	F min.	G	H
ET20	20.1±0.5	20.1±0.5	4.0±0.3	4.4±0.3	15.7	15.7	2±0.2	2±0.2
ET24	24.2±0.5	24.2±0.5	4.0±0.3	4.0±0.3	19	19	2.4±0.15	2.4±0.15
ET28	28.45±0.55	28.45±0.55	5.0±0.3	5.0±0.3	22.2	22.2	2.9±0.2	2.9±0.2
ET29	29±0.4	30±0.4	5±0.3	5±0.3	22.6	23.6	2.9±0.2	2.9±0.2
ET35	35.5±0.6	35.5±0.6	7.5±0.3	7.5±0.3	26.8	26.8	4.0±0.2	4.0±0.2

ET Cores

Broadband transformer
 Current compensated chokes
 Common mode filter

Part number	C1 (mm ⁻¹)	Le (mm)	Ae (mm ²)	Ve (mm ³)	Weight (g)/set	AL(nH/N ²) ± 30%		
						SM070	SM100	SM120
ET20	2.94	50.50	17.20	868.60	4.30	2700	3600	4400
ET24	3.47	60.80	17.50	1064.00	5.40	2700	3600	4400
ET28	2.61	71.40	27.40	1956.36	10.20	3600	4500	5400
ET29	2.67	74.50	27.90	2078.55	10.50	3600	4500	5400
ET35	1.48	86.70	58.60	5080.62	24.50	5000	6400	8500

*All specification are subject to change without notice.

