



Part number	Dimension(mm)							
	A	B	C	D min.	E	F min.	G	H
FT19	19.5±0.3	14.2±0.6	5.0±0.3	6.8	4.0±0.2	12.9	3.2±0.2	3.2±0.2
FT20	20.6±0.3	14.1±0.3	4.6±0.2	7.35	4.2±0.2	15.7	2.4±0.15	2.3±0.15
FT22	21.5±0.3	14.9±0.3	4.5±0.2	7.6	4.2±0.2	15.9	2.8±0.2	2.65±0.15
FT22A	21.5±0.4	15.6±0.3	3.7±0.2	6.7	5.0±0.2	15.2	3.7±0.2	3.0±0.15
FT30	30.0±0.4	19.8±0.3	6.4±0.15	8.9	6.4±0.15	22.6	4.2±0.15	3.55±0.15

FT Cores

Broadband transformer
 Current compensated chokes
 Common mode filter

Part number	C1 (mm ⁻¹)	Le (mm)	Ae (mm ²)	Ve (mm ³)	Weight (g)/set	AL(nH/N ²)±25%		AL(nH/N ²)±30%
						SM050	SM070	SM100
FT19	0.34	17.20	50.30	865.16	4.30	2050	3050	4100
FT20	4.43	53.10	12.00	637.20	3.70	1400	2200	2800
FT22	4.19	56.20	13.40	753.08	4.10	1450	2200	2900
FT22A	4.37	55.10	12.60	694.26	3.70	1430	2150	2850
FT30	0.35	26.80	77.40	2074.32	11.30	2000	3000	4200

*All specification are subject to change without notice.